

## Class-D Mono Amplifier with Bass Boost Remote

**General**

Max.power output	600 W x 1 (4 $\Omega$ ) 1,000 W x 1 (2 $\Omega$ ) 1,600 W x 1 (1 $\Omega$ )
RMS power output	300 W x 1 (4 $\Omega$ ) 500 W x 1 (2 $\Omega$ ) 800 W x 1 (1 $\Omega$ )
Frequency Response	10 Hz to 240 Hz
Impedance	1 $\Omega$ to 8 $\Omega$
Total Harmonic Distortion(THD)	<0.5% (100 Hz)
S/N Ratio	>100 dB
Bass BoostLevel	0 dB to 18 dB